intel®

AP-503

APPLICATION NOTE

Add-in Flash Memory Card for an 80C186EA Application

DR. MAHESH RAO
APPLICATIONS SUPPORT GROUP, ASMO

DAVID BOUD
APPLICATIONS SUPPORT GROUP, ASMO

ANDREW GAFKEN
FLASHCARD DESIGN GROUP, MCD

September 1994

Order Number: 272476-001

Additional copies of this document or other Intel literature may be obtained from:

Intel Corporation
Literature Sales
P.O. Box 7641
Mt. Prospect, IL 60056-7641

or call 1-800-879-4683

CONTENTS

1.0 ABSTRACT

This paper discusses an application of Series 2 Flash memory cards in an embedded 80C186 design. The Series 2 Flash memory cards could be used for data as well as code storage. This paper describes a generalized, low-cost design approach to interfacing Series 2 Flash memory cards with embedded 80C186-based systems to vastly enhance the system's data storage capability, as well as allowing designers to broaden the scope of their applications.

2.0 INTRODUCTION

Engineers face a growing need to produce ROMable code for Intel architecture microprocessors. The low cost, high quality, and availability of standard DOS tools make them attractive candidates for ROMable-code generators [1]. Even though most 80C186 embedded systems do not run under DOS, using DOS-based PCs to develop, test, debug, and port ROMable code would make development easier and cheaper and could considerably reduce time to market. Using Intel Flash memory cards in an 80C186-based embedded system would address the issue of porting the code as well as increasing the addressable memory space [2]. A simple implementation using Intel Flash memory cards in an 80C186-based system is discussed here.

3.0 PCMCIA–186EA INTERFACE

The 80C186 family of embedded processors are highly integrated, 16-bit processors of choice for high-performance embedded applications. The 80C186EA is the second member of the 80C186 modular core family. It is 100% code-compatible with the standard 80C186, but includes two power management modes. Intel offers an 8-bit bus version, called the 80C188EA, as well as 3-volt versions designated the 80L186EA and 80L188EA. Upgrades from the standard 80C186 applications to the 80C186EA microprocessor require no software modifications and, in most cases, little or no hardware modification. The details of upgrade are provided in AP-468 [3].

Intel's Series 2 Flash memory cards facilitate high-performance disk emulation in mobile PCs and dedicated equipment [4]. Series 2 Flash memory cards conform to the Personal Computer Memory Card International Association (PCMCIA 2.0)/Japanese Electronics Industry Development Association (JEIDA 4.1) 68-pin standard, providing electrical and physical compatibility. In addition, the Series 2 Flash memory card is compatible with Intel's Exchangeable Card Architecture (ExCA™ architecture), an open hardware and software system implementation of PCMCIA Release 2.0 that allows portability from system to system, independent of manufacturer.

The Flash memory card's low power consumption, transportability, and compatibility make it an ideal choice for designers in the embedded market. Potential embedded applications include portable or handheld controllers, low-power data acquisition and control systems (DAQM's), systems in harsh environments, and systems that would benefit from solid-state removable memory, to mention just a few. The targeted embedded markets, in general, are those in which addressable memory has been a constraint or those that need to port data to other applications. The 80C186 embedded processor family is being used as the core processor in many embedded applications; however, the 80C186 can directly address a maximum space of 1 Mbyte, which may limit its usage in some applications. The addition of Flash memory cards would broaden the application base of these processors. Along with the power-saving features of the 80C186EA and availability of the 3.3-volt powered 80L186EA, the power saving features of the Series 2 Flash memory cards would definitely find wider application bases in embedded and industrial engineering.

In this example, a simple paging scheme was used to increase the memory addressability of the 80C186-based platform. Page length was fixed to 64 Kbytes. The reasons for using the paging method are simplicity and ease. Also, 64 Kbytes is equal to the segmentation value in 80C186-based systems as well as the page length of the Series 2 Flash memory card. This makes it very attractive to have pages of 64 Kbytes each. The additional overhead for setting up pages is very small compared to the additional space for data storage or code execution, and page set-up changes would be needed only when going to the next 64 Kbyte boundary. For smooth code execution, paging may not be the best solution; however, for data storage, paging is one of the best solutions available.

4.0 HARDWARE

The described add-in board increases the addressable memory space of both existing and future 80C186 platforms, with minor modifications in some cases. Since the add-in board would be based on Series 2 Flash memory cards, the interface would meet the PCMCIA standard. Meeting the PCMCIA standard would increase the 80C186 memory space availability from 1 Mbyte to as high as 64 Mbytes. This add-in board would allow designers to develop, test, and debug software on a DOS-based PC, then download the software to the embedded system using Flash memory cards. In addition, Flash memory cards offer these features:

- They are nonvolatile, so they do not require a battery backup for data retention as SRAM memory subsystems typically do.
- Their power-saving modes allow for power conservation strategies in various operating conditions.
- They can be removed from the field unit and transferred to computer systems for data retrieval and analysis.
- They make it possible to change the operating software.

Figure 1 shows a block diagram of the system and Figure 2 shows the map of memory and input/output devices.



Figure 1. System Block Diagram



Figure 2. Memory and I/O Device Map

The system uses an 82510 serial interface for communicating with the outside world and an 82C55 peripheral interface adapter for memory paging. The system has the following major components:

- 64 Kbytes of SRAM
- 16 Kbytes of program memory (EPROM)
- 64 Kbytes of Flash memory
- a PCMCIA 2.0 interface with addressing capabilities for cards up to 64 Mbytes
- an 82510 serial interface for RS-232C-based communication capabilities
- an 82C55 programmable peripheral interface adapter (PIA)

4.1 Timing Analysis

Series 2 Flash memory cards are offered with various read access times ranging from 150 ns to 250 ns. These times are referenced only to the read cycle; write cycle times are typically longer than read cycle times. The 80C186EA is offered in frequencies of up to 20 MHz, resulting in clock periods of 50 ns (T=50 ns).

Output enable (RD#) to data valid on the Series 2 Flash memory cards is represented by T_{GLOV}, which is a maximum of 100 ns and should be less than $(2+n)T-T_{CLOV2}-T_{CLIS}$ of the 80C186EA; larger values would require wait states. Also, the address valid to data valid time for the 80C186EA is $(3+n)T-T_{CLOV2}-T_{ADLTCH}-T_{CLIS}$, which should be greater than the card's 250 ns address access time, T_{AVOV}. In the equations above, n is the number of wait states to be inserted. With the insertion of each wait state, the 80C186EA's timing would increase by a time equal to one T (50 ns at 20 MHz).

An 80C186EA operating at 20 MHz would require a minimum of three wait states to guarantee reliable read operations for cards with up to 250 ns read access time. It would require one wait state for read operations even for cards with 150 ns read access time. The same number of wait states would also work for write operations because the 80C186EA polls the card to see whether it is ready for the next write.

4.2 PCIC Use

Intel's PC Card Interface Controller (PCIC) is the ExCA™ architecture interface solution for notebook PCs [5]. The 82365SL allows PC manufacturers to design systems that provide a wide range of connection or communication options (modem, Twisted Pair Ethernet, etc.) as well as eliminating rotating electromechanical media (via Intel Flash memory cards). However, the 82365SL was not used in this design, for the following reasons:

- The scope of the project was to interface Flash memory cards to an 80C186-based system, and cost was one consideration. The cost of the 82365SL is greater than that of the 82C55.
- This design would not use the 82365SL's full functionality and capabilities, so the increased system cost would not be justified.
- The complexity of the design using the 82365SL would be greater, in both hardware and software, than that of the proposed design.

4.3 PIA Use

This design implements a solution that is both cost-effective and easy to implement. The design uses multiple ports to set up pages of 64 Kbytes each. The primary page can be mapped to any available 64 Kbyte segment of the 80C186 memory space and the consecutive pages can be set up using the PIA. The parallel interface chosen for this application is Intel's 82C55 Programmable Peripheral Interface Adapter [6]. This CMOS device is inexpensive and easy to program, making it a cost-effective solution. However, using the 82C55 imposes some limitations on the proposed system:

- It limits the maximum page size to 64 Kbytes.
- It requires special memory management software to manage the page frames.

5.0 SOFTWARE

Once the interface hardware was built, firmware was written to test and control the system functionality. This software allows the user to run various tests using a PC or laptop computer. Software initializes the system components such as the 82C55 and 82510 as well as the 80C186EA. Figure 4 shows a flowchart of the system initialization, and Figure 3 shows the interactive menu portion of the software.

```
WELCOME TO PCMCIA-186 INTERFACE
TO CHECK SYSTEM FUNCTIONALITY,
ENTER ANY OF THE FOLLOWING CHOICES.
1. RAM TEST
2. READING FROM PCMCIA CARD
3. WRITING TO PCMCIA CARD
4. EXIT
```

Figure 3. System Menu

The 82510 serial controller is initialized for polled operating mode as described in application note AP-401 [7]. To address the 64 Mbyte address space, the 80C186EA system performs the following steps:

- Sets up the appropriate page address using the 82C55. Each page is 64 Kbytes in length, and the page can be set up by writing to the port.
- Performs the memory read, write, or erase operation in the PCMCIA page address space of the 80C186EA (physical address 50000H).
- Rewrites the page address space of the 82C55 to indicate Page 0.

The above three-step procedure has appropriate messages to indicate the actions taken. The messages are printed to the screen using the 82510 serial controller. However, the task of writing, reading, or erasing the Flash memory card is accomplished by the special memory management software. The flowcharts are shown in Figures 5–8. Also, the system can detect the density and speed of the Series 2 Flash memory cards.

Another advantage of adding Flash memory cards, as mentioned earlier, is that they provide the capability of developing and debugging code remotely and then executing it on an existing platform or system. Also, because Flash memory cards are memory-mapped, it is possible to add new features or change the existing software very easily, either by using the card's memory or by downloading to the system memory. Code can be executed from the PCMCIA card in several ways such as FAR JUMPs, FAR CALLs or RETurn instructions [8].



Figure 4. System Initialization Flowchart



Figure 5. Card-Detect Flowchart

- FAR JUMPs can be used to achieve intrasegment jumps in code. This instruction uses no stack space. The syntax for this instruction is JUMP FAR LABEL *your_label*, where *your_label* is the user's chosen label. However, this allows no direct way to get back to the original location.
- FAR CALLs are just like regular procedure calls, except that they allow intrasegment operation. This instruction uses 4 bytes of stack space for the current Code Segment (CS) and Instruction Pointer (IP) values. The syntax for this instruction is CALL PROC (FAR) or CALL DWORD PTR[reg16]. In this case, a RET instruction at the end will take you back to the previous code segment, if necessary, as the information of the previous CS and IP are stored on the stack.



Figure 6. Read from PCMCIA Card Flowchart

- Using the RET instruction uses the stack only temporarily, to achieve the desired jump. The desired CS and IP are first stored on the stack, then the RET instruction restores the current CS and IP. The syntax for this instruction is RET.

The RET instruction was used in this application. First the new IP and CS, which correspond to the PCMCIA card page value (i.e., CS=5000H and IP=0000H), were saved on the stack, then a RET instruction was executed. This method, as mentioned before, temporarily uses 4 bytes of stack space. Now the code can be executed like any other segment with relocatable code present on the memory card. Again the correct page has to be set up before the RET instruction executes. At the end of the code segment, another RET can be executed to get to the main program. The overhead of a few instructions compared to the 64 Kbyte segment of code is minimal and the performance degradation is also negligible.



Figure 7. Write to PCMCIA Card Flowchart



Figure 8. PCMCIA Card Erase Flowchart

6.0 CONCLUSION

This article describes an 80C186EA–PCMCIA interface design and outlines the advantages of such a design. Software files and drivers can be obtained by calling Intel's applications BBS at 916-356-3600 in the U.S. or at +44(0) 793-496340 in Europe.

REFERENCES

[1]. James D. Broesch, "Standard DOS Tools to Generate ROMable 80x86 code," *EDN*, Jan 7, 1993.

[2]. *Embedded Microcontrollers and Processors, Vol II*, pp. 24-59 thru 24-173. Intel, 1993, Lit. # 210830.

[3]. Larry Bates, "Quick Upgrade from the 80C186 to the 80C186EA," AP-468, Intel, 1991, Lit.# 272157.

[4]. *Memory Products, Series 2 Flash Memory Cards*, Intel, 1993, Lit. # 290434.

[5]. *PC Card Interface Controller*, Intel, 1993, Lit# 290423.

[6]. *Peripherals Components*, pp 3-124 thru 3-146, Intel, 1993, Lit # 231256.

[7]. Faisal Imdad-Haque, "Designing with the 82510 Asynchronous Serial Controller," AP-401, Intel, 1993, Lit. # 231928.

[8]. *iAPX 86, 88, 186 and 188 User's Manual, Programmer's Reference*, Intel, 1986, Lit.# 210911.

APPENDIX A
MONITOR AND CONTROL PROGRAM FOR 186EA–PCMCIA INTERFACE

```
;PCMCIA-186 INTERFACE PROJECT TEST CODE
; MEMORY MAP:
; CHIP        START   STOP     CS#
; 27C64       FE000   FFFFF    UCS#
; 84256       00000   0FFFF    LCS#
; 28F256      60000   6FFFF    MCS2# 1 wait state
; PCMCIA      50000   5FFFF    MCS1# Page starts here
; 82510       0000             PCS0#  IO MAP
; 82C55       0080             PCS1#  IO MAP
; PCBREGISTER     IN IO MAP @ FF00H
;=================================================
;
;Code written in ASSEMBLY ASM86 Intel.
;program invoked by  "ASM86 AP186.ASM LIST"
;*********************************************************
;Set control block register addresses
CNTRL_BLK       EQU       0FF00H; Relocation of PCB at reset
UMCS            EQU       0FFA0H; Upper chip select reg location
LMCS            EQU       0FFA2H; Lower chip select reg location
MMCS            EQU       0FFA6H; Middle chip select reg locations
MPCS            EQU       0FFA8H; Control register for PCS & MCS
PACS            EQU       0FFA4H; Peripheral chip select reg
PWRSAV          EQU       0FFF0H; Power save register
POWRCON         EQU       0FFF2H; Power control register
STEPID          EQU       0FFF6H; Device step ID
RELREG          EQU       0FFFEH; Relocation register
;Base address definition
PCMCIA_BASE     EQU       5000H ; PCMCIA card page start
PCS_BASE        EQU       0000  ; Base address
CODE_BASE       EQU       0FC00H; Code starts here

;Other registers
PCS0            EQU     PCS_BASE; PCS0# select base address
PCS1            EQU     PCS0+128; Address for PCS1#
PCS2            EQU     PCS0+256; Base address for PCS2#
;*********************************************************
;COntrol Register Values And Port Addresses
;Remember the ports are aligned at even addresses
;(A1(OF 186)-> to A0 of parallel port)
;*********************************************************
CLRSCRN       EQU       1AH      ;Clear screen for VT100
CNTR_PIO      EQU       PCS1+6   ;82C55 Control register
PIO_A         EQU       PCS1     ;Port A
PIO_B         EQU       PCS1+2   ;Port B
PIO_C         EQU       PCS1+4   ;Port C
SIO_BAUD_LO   EQU       PCS0     ;Baud low register (DLAB=1)
SIO_GER       EQU       PCS0+2   ;General purpose enable register(BANK=0)
```

```
SIO_GIR       EQU       PCS0+4   ;Interrupt control/bank register(BANK=0)
SIO_LCR       EQU       PCS0+6   ;Line configuration register(BANK=0)
SIO_DATA      EQU       PCS0     ;Data port for RXD and TXD (BANK=1)
SIO_GSR       EQU       PCS0+14  ;General status register (BANK=1)
SIO_ICM       EQU       PCS0+14  ;Internal command register (BANK=1)
SIO_FMD       EQU       PCS0+2   ;TxFIFO=0, RxFIFO=0 (BANK=2)
SIO_TMD       EQU       PCS0+6   ;Modem automatic (BANK=2)
SIO_RMD       EQU       PCS0+14  ;Rx Mc mode register (BANK=2)
SIO_IMD       EQU       PCS0+8   ;General status register(BANK=2)
SIO_RIE       EQU       PCS0+12  ;Rx Intr enable reg (BANK=2)
SIO_CLCF      EQU       PCS0     ;Clock configuration register (BANK=3)
SIO_BACF      EQU       PCS0+2   ;BRGA config reg
SIO_BBCF      EQU       PCS0+6   ;BRGB config reg
;*************************************************************
;
;Definition of register values and constants
;1 Wait state for memory
;3 (max) Wait states for IO
;*************************************************************
UMCS_VAL        EQU     0FC38H  ;16 KByte blocks
LMCS_VAL        EQU     0FFCH   ;64 KByte blocks
MPCS_VAL        EQU     0A0BFH  ;64 KByte MCSn chip-select blocks
MMCS_VAL        EQU     41FDH   ;Start address of MCSn BLOCK=20000H
PACS_VAL        EQU     003FH   ;Start address of PCSn BLOCK=0000H

;OTHER CONTROL VALUES
PIO_VAL         EQU     89H     ;Set up for 82C55
SIO_IMD_VAL     EQU     0CH     ;IAM=1, RFD=1
SIO_LCRD_VAL    EQU     83H     ;DLAB=1
SIO_LCR_VAL     EQU     03H     ;DLAB=0, 8 BIT 16X, NP, 4/4 MODE
SIO_RMD_VAL     EQU     10H     ;SAMPL WINDOW=7/16
SIO_CLCF_VAL    EQU     50H     ;16x MODE, RxCS=TxCS=BRGA
SIO_BAL_VAL     EQU     3CH     ;DLAB=1: 9600 BAUD, (BAH=0 DEFAULT)
SIO_GER_VAL     EQU     07H     ;Tx disable, Rx enable intr
SIO_RIE_VAL     EQU     0       ;Disable all functions
SIO_GIR1_VAL    EQU     21H     ;Bank 1
SIO_GIR2_VAL    EQU     41H     ;Bank 2
SIO_GIR3_VAL    EQU     61H     ;Bank 3
SIO_BACF_VAL    EQU     04      ;BRGA mode
SIO_BBCF_VAL    EQU     04      ;BRG mode
SIO_ICM_VAL     EQU     10H     ;Software reset

;CONSTANTS
CR              EQU     0DH                 ;Carriage return
LF              EQU     0AH                 ;Line feed
EOT             EQU     04H                 ;End of text, ASCII stopper
EOL             EQU     0A0DH               ;LF, CR
TOS             EQU     0FFFFH              ;Top of stack at top of RAM
RAM_BASE        EQU     1024                ;Usable RAM starts here
RAMTOP_USE      EQU     TOS-50H             ;Usable RAMTOP area
RAM_COUNT       EQU     RAMTOP_USE-RAM_BASE ;Actual RAM count
INMSG           EQU     RAM_BASE+1          ;Save input value
CMDSTAT         EQU     00H
PAGE_STORE      EQU     410H
PAGE_NUM_VAL    EQU     PAGE_STORE+40H
PAGE_NUMBR      EQU     PAGE_NUM_VAL+10
```

```
PAGE_SIZE       EQU     PAGE_NUMBR+4
CD_SP_VAL       EQU     PAGE_STORE+2
CD_SZ_VAL       EQU     CD_SP_VAL+1

     CODE SEGMENT AT 0FC00H

     ASSUME CS:CODE, DS:CODE
INIT:
;*************************************************************
;                                                            *
;     Entry Point On Power Up                                *
;                                                            *
;*************************************************************

FW_START  LABEL   FAR      ;Forces far jump
     CLI                   ;Disable Interrupts
     MOV AX, 0             ;Intialize data segment to 00000
     MOV DS, AX            ;DS=00000
     MOV ES, AX            ;ES=00000
     MOV SS, AX            ;SS=00000
     MOV AX, TOS           ;SP=FFFFH
     MOV SP, AX

;-------------------------------------------------------------
;Initialization of stack is done; STACK=0FFFFH
;Set up chip selects
;
;UCS - EPROM Select  (Initialized during POWER_ON code)
;LCS - SRAM  Select  (Set to SRAM Size)
;PCS - I/O   Select  (PCS0-1 Support 82C55 AND 82510)
;MCS0 -FLASH Select  (Set to 64 Kbyte Size)
;MCS1  PCMCIA Select (Set to 64 Kbyte Size)
;-------------------------------------------------------------
     MOV  DX, LMCS         ;Set up LCS Register
     MOV  AX, LMCS_VAL
     OUT  DX, AL           ;Remember, byte writes OK

     MOV  DX, MPCS         ;Ready for PCS lines 0-1
     MOV  AX, MPCS_VAL     ;As well as MCS programming
     OUT  DX, AL

     MOV  DX, MMCS         ;Set up  PCMCIA-FLASH chip-select
     MOV  AX, MMCS_VAL
     OUT  DX, AL

     MOV  DX, PACS         ;Set up I/O chip-select
     MOV  AX, PACS_VAL
     OUT  DX, AL

;*********************************************************************
;FILL_A and B interrupt vectors point to unwanted interrupt so that
;stray interrupts won't cause the board to hang
;Verify that DS=00000H
;*********************************************************************
     MOV     DI, 0                  ;Start at 0
     MOV     CX, 256                ;Do 256 times
```

```
FILL_A:
     MOV     [DI], OFFSET UNWANTED_INT
     ADD     DI, 4                   ;Fill offsets
     LOOP    FILL_A                  ;IP=Offset

     MOV     DI, 2                   ;Start at 2
     MOV     CX, 256                 ;Do 256 times
     MOV     AX, CODE_BASE           :Equate CS=0FC00H
FILL_B:
     MOV     [DI], AX
     ADD     DI, 4                   ;Fill CS segments
     LOOP    FILL_B


;*********************************************************************
; Set Up PCMCIA-186 INTERRUPT VECTORS
;
;Set up Vector 6 to point to routine that catches the execution of
;unknown opcodes.  This routine is especially important when debugging
;new code since it is possible that the new code can vector off into
;never-never land.
;*********************************************************************
     MOV     DI, 4*6                   ;Point to Vector 6 (unused Opcode)
     MOV     [DI], OFFSET OPCODE_TRAP  ;Load offset
     MOV     [DI+2],  AX               ;Load segment

;*******************************************************
;Initialize parallel I/O
;82C55 is at $80, connects to PCS1, no interrupts, direct
;polling
;*******************************************************
     CALL PIO_INIT           ;Call parallel I/O initialize

;*******************************************************
;Initialize Serial I/O
;82510 is at $0, connects to PCS0, receive and
;transmit are polled.
;*******************************************************
     CALL SIO_INIT          ;Call Initialize Serial IO
;*************************************************************
; Output a Menu to the Screen
;*************************************************************
     STI                    ;Enable all interrupts
SCRN_MENU:
     EVEN
     MOV     AX, TOS        ;Re-initialize the SP
     MOV     SP, AX
     MOV     AX, CODE_BASE  ;Re-initialize the DS
     MOV     DS, AX         ;register. DS=CS
     LEA     BX, MENU_MSG   ;Get bad input message
     CALL    CARD_PRINT     ;Print to the screen
;*********************************************************************
; What is the Keyboard Input?
;*********************************************************************
     MOV     BX, INMSG
     CALL    RECEIVE              ;Get the character
```

```
     MOV     [BX], AL             ;Check the input value
     CALL    TRANSMIT             ;Echo back the character
     CMP     AL, '1'              ;Is it one?
     JZ      RAMTEST              ;If so, it is RAM test
     CMP     AL, '2'              ;Is it two?
     JZ      RD_PCMCIA            ;Read from PCMCIA card
     CMP     AL, '3'              ;Is it 3?
     JZ      WR_PCMCIA            ;Write to PCMCIA card
     CMP     AL, '4'              ;Get out?
     JZ      LOOP_HALT            ;Halt
     LEA     BX, BAD_INPUT_MSG    ;Get bad input message
     CALL    CARD_PRINT           ;Print the message to screen
     CALL    DELAY                ;Wait for some time
     JMP     SCRN_MENU            ;Go back and output a message to screen
LOOP_HALT:
     LEA     BX, HALT_MSG         ;Load halt message to the pointer
     CALL    CARD_PRINT           ;Print to screen
     CALL    DELAY                ;Wait for some time
     HLT                          ;System halted

;*************************************************************
; Checkerboard RAM Test Routine
;*************************************************************
RAMTEST:
     EVEN
     CALL    RAM_TEST             ;Test the locations
     CALL    DELAY                ;Wait for some time
     JMP     SCRN_MENU            ;Go back to the menu

;*************************************************************
; PCMCIA Read Routine
;*************************************************************
RD_PCMCIA:
     EVEN
     CALL    CARD_DETECT         ;Detect card presence?
     CALL    PAGE_INPUT          ;Get the page #'s
     CALL    RDPCMCIA
     JMP     SCRN_MENU           ;Go back to screen menu

;*************************************************************
; PCMCIA Write Routine
;*************************************************************
WR_PCMCIA:
     EVEN
     CALL    CARD_DETECT        ;Valid card?
     CALL    PAGE_INPUT         ;Get the page #'s
     CALL    CARD_ERASE
     CALL    WRPCMCIA
     JMP     SCRN_MENU          ;Go back to screen menu

;*************************************************************
; A simple delay routine provides time to read messages
; (uses CX)
;*************************************************************
DELAY:
     EVEN
```

```
     PUSH    AX              ;Save registers
     PUSH    CX
     PUSH    DS
     XOR     AX, AX          ;Clear AX
     XOR     CX, CX          ;Clear CX
     MOV     DS, AX          ;Clear DS
LOOP_DELAY:
     DEC     CX              ;Decrement CX
     NOP                     ;Increase delay value
     NOP
     CMP     CX, AX          ;Is CX=AX?
     JNZ     LOOP_DELAY      ;If not,loop back
     POP     DS
     POP     CX              ;Restore values
     POP     AX
     RET

;************************************************************
; This subroutine gets the page number, modifies the input,
; and prints an appropriate message.
; Calls GET_PAGE
;   Converts the input ASCII value to hex
;   Page # in hex is less than 400H.
;   Returns the value in AX.
; Calls CARD_PRINT
;************************************************************
     EVEN
PAGE_INPUT:
     PUSH    AX
     PUSH    DS                ;Save registers
     XOR     AX, AX
     MOV     DS, AX
     CALL    NEXT_LINE         ;Print a blank line
     LEA     BX, PG_NUM_MSG    ;Output first message
     CALL    CARD_PRINT        ;to screen
     MOV     BX, PAGE_NUM_VAL  ;Store page numbers
     CALL    GET_PAGE          ;Get multiple characters
     MOV     BX, PAGE_NUMBR    ;Get the actual value
     MOV     AX, [BX]          ;to set up page
     CMP     AX, 'MR'          ;Is it bad page input?
     JZ      OUT_BAD           ;Get out
     MOV     DX, PIO_A         ;Port A
     OUT     DX, AL
     MOV     DX, PIO_B         ;Port B
     IN      AL, DX
     AND     AL, 80H           ;Save REGB# input
     OR      AL, AH            ;Get high byte
     OUT     DX, AL            ;Set up Port B
     POP     DS
     POP     AX
     RET
OUT_BAD:
     POP     DS
     POP     AX                ;Get out of this subroutine and
     JMP     SCRN_MENU         ;to the main routine
;*********************************************
```

```
; Subroutine GET_PAGE
; Gets the values from keyboard and echos back
; Converts ASCII to hex
; ******************************************
GET_PAGE:
     PUSH    AX              ;Save accumulator
     PUSH    CX              ;Save count reg
     MOV     CX, 0           ;Start count
PGNUMLP:
     CALL    RECEIVE         ;Get character
     MOV     [BX], AL        ;Save the value
     CALL    TRANSMIT        ;Transmit the value
     INC     BX              ;Increment pointer
     INC     CX              ;Increment count
     CMP     AL, CR          ;Is it the end?
     JNZ     PGNUMLP         ;If not, loop back
     MOV     AL, EOT         ;Store control char
     MOV     [BX], AL
     MOV     BX, PAGE_NUM_VAL;Start conversion
     MOV     AX, 0H          ;Clear AX
     MOV     DX, 0           ;Clear DX
     CMP     CX, 04
     JNZ     BAD_PAGE        ;If not, page is bad
     ADD     BX, 2           ;Add 2
     CALL    ASC_HEX
     MOV     DL, AL          ;Move it to DL
     DEC     BX
     CALL    ASC_HEX
     SHL     AL, 4           ;Shift left four times
     MOV     DH, AL          ;
     DEC     BX
     CALL    ASC_HEX
     MOV     AH, AL          ;Get the high byte
     MOV     AL,0
     OR      AL, DH          ;Get second nibble
     OR      AL, DL          ;Make it one word
     MOV     BX, PAGE_NUMBR  ;Get page number place
     MOV     [BX], AX        ;Store the value
     MOV     BX, PAGE_SIZE   ;Get the card size value
     MOV     CX, [BX]        ;Get the value of CX
     CMP     AX, CX          ;Compare the values
     JG      BAD_PAGE
     JMP     GET_IP_END      ;Go to end
BAD_PAGE:
     MOV     AX, 'MR'        ;If bad put sign
     MOV     BX, PAGE_NUMBR  ;Get page number place
     MOV     [BX], AX        ;Store sign
     LEA     BX, BAD_PG_MSG  ;Bad page message
     CALL    CARD_PRINT      ;Print the message
     JMP     SCRN_MENU
GET_IP_END:
     POP     CX
     POP     AX              ;Restore regs
     RET                     ;Return
;*********************************************************
; ASC_HEX converts the received characters to hex
```

```
;************************************************************
ASC_HEX:
     MOV     AL, [BX]        ;Get the data
     SUB     AL, '0'         ;Take out 30H
     CMP     AL, 09H         ;Is it between 0-9, inclusive?
     JG      ASC_LP
     JMP     ASC_END         ;Else, go to end
ASC_LP: SUB     AL, 07       ;Else, subtract 7
ASC_END:RET
;************************************************************
; Transmit a character using 82510
; Nothing returned
; Nothing modified
;************************************************************

     EVEN
TRANSMIT:
     PUSH    CX                      ;Save CX register
     PUSH    DS
     XOR     CX, CX                  ;Clear CX register
     MOV     DS, CX                  ;Load ES to point to RISM memory
     MOV     CX, AX                  ;Save copy of AX
TR_ST_LOOP:
     MOV     DX, SIO_GSR             ;Check transmit buffer
     IN      AL, DX                  ;Get the status data
     TEST    AL, 10H                 ;Save TxM status
     JE      TR_ST_LOOP              ;If not, loop
     MOV     AX, CX                  ;Copy back value
     MOV     DX, SIO_DATA            ;Setup to output to 82510 data port
     OUT     DX, AL                  ;Write the data to the 82510
     POP     DS
     POP     CX                      ;Restore stack
     RET                             ;Return home
;*****************************************************
;Subroutine to Print Next Line
;*****************************************************
NEXT_LINE:

     MOV     AX, EOL                 ;Move EOL data into AX
     CALL    TRANSMIT                ;Send out the data in AL
     MOV     AL, AH                  ;Copy AH into AL
     CALL    TRANSMIT                ;Send out the data in AL
     RET
;************************************************************
; Receive a character using 82510
; Returns:
; Nothing modified
;************************************************************

     EVEN
RECEIVE:
     PUSH    DS
     XOR     AX, AX                  ;Clear AX
     MOV     DS, AX                  ;DS=0000H

RX_ST_LOOP:
```

```
     MOV     DX, SIO_GSR             ;Check receive buff
     IN      AL, DX                  ;Get the status data
     TEST    AL, 04H                 ;Save RxM status
     JNE     RX_ST1_LOOP             ;If not, loop
     TEST    AL, 01H                 ;Save RxM status
     JE      RX_ST_LOOP              ;If not, loop
RX_ST1_LOOP:
     MOV     DX, SIO_DATA            ;Setup to output to 510 data port
     IN      AL, DX                  ;Get the data
     POP     DS                      ;Restore stack
     RET                             ;Return home
;*****************************************************
; Checkerboard RAM Test
;*****************************************************
RAM_TEST:
     EVEN
     PUSH    AX                      ;Save contents
     PUSH    BX
     PUSH    CX
     PUSH    DS
     XOR     AX, AX                  ;AX=0
     MOV     DS, AX                  ;Reload data segment
     MOV     AX, 5555H               ;Load the checkerboard pattern
LOOP2:
     MOV     DX, AX                  ;Make a copy in DX
     MOV     BX, RAM_BASE+1          ;Load start address into BX
     MOV     CX, RAM_COUNT           ;Load count value into CX
     CLD
RT_LP:
     MOV     [BX], AX               ;Write data to the RAM
     MOV     AX, [BX]               ;Copy back
     CMP     AX, DX                 ;Compare AX to DX
     JE      EQUAL                  ;If equal, jump
     JMP     BAD_RAM                ;If not, go to bad RAM message
EQUAL:
     INC     BX
     LOOPNE  RT_LP                  ;Else loop
     CLC                            ;Clear carry
     RCL     AX, 1                  ;Repeat checkerboard test
     CMP     AX, 5554H              ;Is it done with two loops?
     JE      DONE                   ;If so, go to done
     JMP     LOOP2                  ;Else, loop back
DONE:
     LEA     BX, RAM_OK_MSG         ;Output RAM OK message
     CALL    CARD_PRINT             ;to screen
     POP     DS
     POP     CX
     POP     BX
     POP     AX
     RET

BAD_RAM:
;*******************************************************
; Output "RAM bad message" to the screen,
; call card-print and  halt the system
;*******************************************************
```

```
     LEA     BX, BAD_RAM_MSG ;Output message
     CALL    CARD_PRINT      ;Output characters to screen
     HLT

;************************************************************
;
; Card-detect Routine
; Checks to see whether if a valid card is present
; If card is detected, Print Intel series 2 message to screen
; Message will be modified to present speed and density info.
;************************************************************
     EVEN
CARD_DETECT:
     PUSH    AX              ;Save accumulator
     PUSH    DS              ;Save data seg
     XOR     AX, AX          ;Load accum with zero
     MOV     DS, AX          ;DS points to zero
     CALL    NEXT_LINE       ;Go to next line to print
     MOV     DX, PIO_C       ;Set up for Port C of PIA
     IN      AL, DX          ;Get the data
     AND     AL, 11000000B   ;Save CD1, CD2
     CMP     AL, 80H         ;Are they one?
     JNZ     CFLMSG          ;If not zero, go to card fail
     MOV     DX, PIO_B       ;Point to Port B
     MOV     AL, 0
     OUT     DX, AL          ;Reg#=0
     MOV     DX, PIO_A       ;Point to Port A
     OUT     DX, AL          ;Page=0
     MOV     AX, PCMCIA_BASE ;Load base address of PCMCIA card
     MOV     ES, AX          ;Load extra segment with base
     MOV     CX, 35          ;Load count value
     MOV     SI, 00H         ;Load source pointer
     MOV     DI, PAGE_STORE  ;Load destination address
     STD
CD_LOOP1:
     MOV     AX, ES:[SI]     ;Get the data
     MOV     DS:[DI], AL     ;Save low byte
     ADD     SI, 2
     INC     DI
     LOOP    CD_LOOP1        ;Finish loop
     MOV     AX, EOL         ;Save EOL
     MOV     DS:[DI], AX
     ADD     DI, 2
     MOV     AL, EOT
     MOV     DS:[DI], AL     ;Load control characters
     MOV     BX, CD_SZ_VAL   ;Get data
     CALL    CARD_SIZE       ;Get card density
     MOV     BX, CD_SP_VAL   ;Get data
     CALL    CARD_SPEED      ;Get card speed
     MOV     BX, PAGE_STORE  ;Get data
     ADD     BX, 21          ;Card manufacturer msg
     MOV     AL, [BX]        ;Get next character
CD_TR:  CALL    TRANSMIT     ;Transmit characters
     INC     BX              ;Increment pointer
     MOV     AL, [BX]        ;Get next character
     CMP     AL, EOT         ;Is it the end?
```

```
     JNZ     CD_TR           ;Transmit loop
     POP     DS              ;Get back DS
     JMP     CD_END          ;End of card detect

CFLMSG:
     POP     DS              ;Save data seg.
     LEA     BX, MSG_FAIL    ;Load message to indicate PCMCIA
     MOV     AL, [BX]        ;Card not present
CFLTR:  CALL    TRANSMIT     ;Transmit characters
     INC     BX              ;Increment pointer
     MOV     AL, [BX]        ;Get next character
     CMP     AL, EOT         ;Is it the end?
     JNZ     CFLTR           ;Transmit loop
     JMP     SCRN_MENU       ;Do the message
CD_END:
     MOV     DX, PIO_B       ;Point to Port B
     MOV     AL, 80H
     OUT     DX, AL          ;Reg#=1
     POP     AX
     RET
;************************************************
; Compare the card speed and output proper message
;************************************************
CARD_SPEED:
     PUSH    DS
     MOV     AL, [BX]        ;Card present?
     MOV     AH, AL          ;Save a copy
     CMP     AL, 52H         ;Is it 200ns?
     JZ      CARD_T0NS
     MOV     AL, AH          ;Copy back
     CMP     AL, 51H         ;Is it 250ns?
     JZ      CARD_TFNS       ;Jump to 250ns message
     MOV     AL, AH          ;Copy back
     CMP     AL, 53H         ;Is it 150ns?
     JNZ     CARD_UNKNWN     ;Else, output card unknown message
     LEA     BX, CARD_150    ;Load card message
     CALL    CARD_PRINT      ;Print the message
     JMP     CD_SPEND        ;End of card detect
CARD_T0NS:
     LEA     BX, CARD_200    ;Load card message
     CALL    CARD_PRINT      ;Print card message
     JMP     CD_SPEND        ;End of card detect
CARD_TFNS:
     LEA     BX, CARD_250    ;Load card message
     CALL    CARD_PRINT
     JMP     CD_SPEND        ;End of card detect
CARD_UNKNWN:
     LEA     BX, UNKNWN_MSG  ;
     CALL    CARD_PRINT
     JMP     SCRN_MENU
CD_SPEND:
     POP     DS
     RET
;************************************************
; Card-size Check Routine
;************************************************
```

```
CARD_SIZE:
     PUSH    DS              ;Save segment
     MOV     AL, [BX]        ;Get data into AL
     MOV     AH, AL          ;Copy AL
     MOV     BX, PAGE_SIZE   ;Store value at pointer
     CMP     AL, 06H         ;Is it 2M?
     JE      CD_2MEG
     CMP     AL, 0EH         ;Is it 4M?
     JE      CD_4MEG
     CMP     AL, 16H         ;Is it 6M?
     JE      CD_6MEG
     CMP     AL, 1EH         ;Is it 8M?
     JE      CD_8MEG
     CMP     AL, 26H         ;Is it 10M?
     JE      CD_10MEG
     CMP     AL, 2EH         ;Is it 12M?
     JE      CD_12MEG
     CMP     AL, 3EH         ;Is it 16M?
     JE      CD_16MEG
     CMP     AL, 4EH         ;Is it 20M?
     JE      cd_20MEG

CD_UNKNSZ:
     LEA     BX, CARD_MISZ   ;Get mis-size msg
     CALL    CARD_PRINT      ;Print the message
     JMP     SCRN_MENU

CD_2MEG:
     MOV     AX, 10H*2-1     ;# of pages in 2M minus 1
     MOV     [BX], AX
     LEA     BX, CARD_2MEG   ;Get 2M message
     JE      SIZE_END
CD_4MEG:
     MOV     AX, 10H*4-1     ;# of pages in 4M minus 1
     MOV     [BX], AX
     LEA     BX, CARD_4MEG   ;Get 4M message
     JE      SIZE_END
CD_6MEG:
     MOV     AX, 10H*6-1     ;# of pages in 6M minus 1
     MOV     [BX], AX
     LEA     BX, CARD_6MEG   ;Get 6M message
     JE      SIZE_END
CD_8MEG:
     MOV     AX, 10H*8-1     ;# of pages in 8M minus 1
     MOV     [BX], AX
     LEA     BX, CARD_8MEG   ;Get 8M message
     JE      SIZE_END
CD_10MEG:
     MOV     AX, 10H*10-1    ;# of pages in 10M minus 1
     MOV     [BX], AX
     LEA     BX, CARD_10MEG  ;Get 10M message
     JE      SIZE_END
CD_12MEG:
     MOV     AX, 10H*12-1    ;# of pages in 12M minus 1
     MOV     [BX], AX
     LEA     BX, CARD_12MEG  ;Get 12M message
```

```
     JE      SIZE_END
CD_16MEG:
     MOV     AX, 10H*16-1    ;# of pages in 16M minus 1
     MOV     [BX], AX
     LEA     BX, CARD_16MEG  ;Get 16M message
     JE      SIZE_END
CD_20MEG:
     MOV     AX, 10H*20-1    ;# of pages in 20M minus 1
     MOV     [BX], AX
     LEA     BX, CARD_20MEG  ;Get 20M message
     JE      SIZE_END

SIZE_END:
     CALL    CARD_PRINT      ;Print the message
     POP     DS
     RET
;*********************************************
; Print the Card Message Routine
;*********************************************
CARD_PRINT:
     PUSH    DS
     MOV     AX, CODE_BASE   ;CS SEG address
     MOV     DS, AX          ;Get DS straight
     MOV     AL, [BX]        ;Get next character
PR_LP1: CALL    TRANSMIT     ;Transmit characters
     INC     BX              ;Increment pointer
     MOV     AL, [BX]        ;Get next character
     CMP     AL, EOT         ;Is it the end?
     JNZ     PR_LP1          ;Transmit loop
     CALL    NEXT_LINE       ;
     POP     DS
     RET


;*****************************************************
; Card-erase Routine
;*****************************************************
     EVEN
CARD_ERASE:
     PUSH    DS
     PUSH    AX
     MOV     DX, PIO_B
     MOV     AL, 80H
     OUT     DX, AL          ;Reg#=1
     MOV     AX, PCMCIA_BASE ;Get the base address
     MOV     DS, AX          ;Reset DS
     MOV     AX, 2020H       ;Set up for erase
     MOV     DI, 0           ;Set up destination pointer
     MOV     [DI], AX        ;Start erase
     MOV     AX, 0D0D0H      ;Erase confirm
     MOV     [DI], AX        ;
     MOV     CX, 0           ;Get a copy reg ready
     MOV     DX, PIO_C       ;Get Port C address
ER_LP1: IN      AL, DX       ;Get Port C value
     MOV     AH, AL          ;Make a copy
     AND     AL, 00001000B   ;RDY/BSY#=1?
```

```
     CMP     AL, 08H
     JNZ     ER_LP1          ;Keep looping
     MOV     AX, [DI]        ;Get it to AX
     AND     AX, 2020H       ;Erase done?
     CMP     AX, 2020H       ;
     JZ      NO_ERASE        ;If so, erase is not done
     MOV     AX, 0FFFFH      ;Check status
     MOV     [DI], AX        ;Reg of PCMCIA card
     MOV     AX, 5050H       ;Get the cntrl word
     MOV     [DI], AX        ;Get it out
     LEA     BX, ER_SUC_MSG  ;Load erase done message
     CALL    CARD_PRINT      ;Print it to screen
     POP     AX
     POP     DS
     RET
NO_ERASE:
     LEA     BX, ER_UN_MSG   ;Load unsuccessful message
     CALL    CARD_PRINT      ;Print it to screen
     POP     AX
     POP     DS
     JMP     SCRN_MENU       ;Go back to start

;*****************************************************
;This routine reads out of the PCMCIA card.
;Now it just send out a card-not-present message.
;*****************************************************
RDPCMCIA:
     PUSH    DS              ;Save data segment
     PUSH    AX              ;Save accumulator
     MOV     DX, PIO_B       ;Set up reg#=1
     IN      AL, DX          ;Get the present value
     MOV     AH, 80H         ;
     OR      AL, AH          ;
     OUT     DX, AL          ;Output the modified value
     MOV     AX, PCMCIA_BASE ;Load PCMCIA base
     MOV     DS, AX          ;Load DS
     MOV     AX, 0FFFFH      ;
     MOV     SI, 0           ;Reset source pointer
     MOV     [SI], AX        ;Ready the card for read
     MOV     CX, 3FFH        ;Start the count
RD_LP1: MOV     AX, [SI]     ;Start  reading
     CALL    TRANSMIT        ;Put it to screen
     MOV     AL, AH          ;Get high byte
     CALL    TRANSMIT        ;
     ADD     SI, 2           ;Add to pointer
     LOOP    RD_LP1          ;Get back
     CALL    NEXT_LINE
     LEA     BX, RD_MSG      ;Read success
     CALL    CARD_PRINT      ;Print this to screen
     MOV     AX, 0FFFFH      ;
     MOV     SI, 0           ;Reset source pointer
     MOV     [SI], AX        ;Ready the card for next read
     POP     AX
     POP     DS
     RET
;*****************************************************
```

```
;This routine writes from the PCMCIA card.
;Now it just send out a card not present message.
;*******************************************************
WRPCMCIA:
     PUSH    DS              ;Save data segment
     PUSH    AX              ;Save accumulator
     MOV     DX, PIO_B       ;Set up reg#=1
     IN      AL, DX          ;Get the present value
     MOV     AH, 80H         ;
     OR      AL, AH          ;
     OUT     DX, AL          ;Output the modified value
     MOV     AX, PCMCIA_BASE ;Load ES with destination
     MOV     DS, AX
     MOV     AX, CODE_BASE   ;Get the source pointer
     MOV     ES, AX
     LEA     SI, MENU_MSG    ;Load the source value
     MOV     DI, 0           ;Start address of destination
     MOV     BX, 0
     MOV     AX, 0FFFFH
     MOV     [BX], AX
     MOV     CX, MSG_COUNT   ;Load the count value
WR_LP1: MOV     AX, 4040H    ;Set up for write
     MOV     [BX], AX        ;Write command
     MOV     AX, ES:[SI]     ;Get the data
     MOV     DS:[DI], AX     ;Save word
     ADD     SI, 2
     ADD     DI, 2           ;Next location
     MOV     DX, PIO_C       ;Get Port C input
WR_LP0: IN      AL, DX       ;Is RDY/BSY#=1?
     AND     AL, 8
     CMP     AL, 08H
     JNZ     WR_LP0          ;If not, loop
     MOV     AX, 7070H       ;Read status reg
     MOV     [BX], AX        ;Write
     MOV     AX, [BX]        ;Read status
     AND     AX, 1010H       ;Write status?
     CMP     AX, 1010H       ;Has it written properly
     JZ      NO_WRITE        ;Else, no write
     LOOP    WR_LP1          ;Finish loop
     MOV     AX, 0FFFFH      ;
     MOV     [BX], AX        ;Ready for read
     LEA     BX, WR_DONE_MSG ;
     CALL    CARD_PRINT      ;Done message
     POP     AX
     POP     DX
     RET
NO_WRITE:
     POP     AX
     POP     DS
     LEA     BX, NO_WR_MSG   ;Unsuccessful message
     CALL    CARD_PRINT
     JMP     SCRN_MENU       ;Go to screen menu

;*******************************************************
;This procedure initializes the parallel I/O.
;82C55 set up in mode 0
```

```
;Port A, B output ports (latched)
;Port C input port (not latched)
;*******************************************************
PIO_INIT:
     PUSH DS                ;Save DS
     XOR  AX, AX            ;Clear AX register
     MOV  DS, AX            ;Re-initialize DS
     MOV DX, CNTR_PIO       ;Load pointer
     MOV AX, PIO_VAL        ;82C55 set up complete
     OUT DX, AL
     MOV AL, 0              ;Output 0'S to the ports
     MOV DX, PIO_A          ;Load Port A to pointer
     OUT DX,  AL            ;Port A, Port B are outputs
     ADD DX, 2
     OUT DX, AL
     POP  DS
     RET
;*********************************************************
; This procedure initializes the serial I/O.
; 82510 set-up in polled mode for
;    receive operation only
; No buffer space for Rx and Tx
; Baud rate=9600
; N 8 1 mode
; Initialize 82510
;*********************************************************
SIO_INIT:
     PUSH    DS                     ;Save DS
     XOR     AX, AX                 ;Re-initilize DS
     MOV     DS, AX
     MOV     DX, SIO_GIR            ;Switch to bank 1
     MOV     AX, SIO_GIR1_VAL       ;Prepare for reset
     OUT     DX, AL
     MOV     DX, SIO_ICM
     MOV     AL, SIO_ICM_VAL        ;Do a software reset
     OUT     DX, AL
     MOV     DX, SIO_LCR            ;Set up communication parameters
     MOV     AL, SIO_LCRD_VAL       ;No parity, 1 stop, 8-bit char
     OUT     DX, AL
     MOV     DX, SIO_BAUD_LO        ;Set up bal register
     MOV     AL, 3CH                ;Low part of 9600 baud
     OUT     DX, AL
     MOV     DX, SIO_LCR            ;DLAB=0
     MOV     AL, SIO_LCR_VAL        ;8 Data bits
     OUT     DX, AL
     MOV     DX, SIO_GIR            ;Switch to bank 2
     MOV     AL, SIO_GIR2_VAL
     OUT     DX, AL
     MOV     DX, SIO_FMD            ;TxFIFO=0, RxFIFO=0
     MOV     AL, 0
     OUT     DX, AL
     MOV     AL, 18H
     MOV     DX, SIO_TMD            ;Automatic mode for modem
     OUT     DX, AL
     MOV     DX, SIO_IMD
     MOV     AL, SIO_IMD_VAL        ;IAM=1, RFD=1
```

```
     OUT     DX, AL
     MOV     DX, SIO_RIE
     MOV     AL, SIO_RIE_VAL         ;Disable all functions
     OUT     DX, AL
     MOV     DX, SIO_RMD
     MOV     AL, SIO_RMD_VAL         ;Sample window=7/16th
     OUT     DX, AL
     MOV     DX, SIO_GIR             ;Switch to bank 3
     MOV     AL, SIO_GIR3_VAL
     OUT     DX, AL
     MOV     DX, SIO_CLCF            ;Set up clock configuration reg
     MOV     AL, SIO_CLCF_VAL        ;16X mode, BRGA Output
     OUT     DX, AL
     MOV     DX, SIO_BACF            ;Set up BRGA configuration reg
     MOV     AL, SIO_BACF_VAL        ;BRGA mode
     OUT     DX, AL
     MOV     DX, SIO_BBCF            ;Set up BRGB configuration reg
     MOV     AL, SIO_BBCF_VAL        ;BRG mode
     OUT     DX, AL
     MOV     DX, SIO_GIR             ;Switch to bank 0
     MOV     AL, 01
     OUT     DX, AL
     MOV     DX, SIO_GER             ;Enable Rx, Tx interrupts
     MOV     AL, SIO_GER_VAL         ;INT0 interrupts are now enabled
     OUT     DX, AL
     MOV     AL, SIO_GIR1_VAL
     MOV     DX, SIO_GIR             ;Switching to bank 1
     OUT     DX, AL
     POP     DS
     RET                             ;Return from initialization

;*************************************************
;Unwanted interrupts have occurred
;output a simple message and halt
;*************************************************
UNWANTED_INT:
     PUSH    AX              ;Save used registers
     PUSH    DX              ;Screw up in code
     LEA     BX, BAD_INT_MSG ;Output message
     MOV     AL, [BX]        ;Get characters
BINT_TRLP:
     MOV     DX, SIO_DATA    ;Set up to output to 510 data port
     OUT     DX, AL          ;Write the data to the 510
     INC     BX              ;Increment pointer
     MOV     AL, [BX]        ;Get next character
     TEST    AL, EOT         ;Is it the end?
     JNZ     BINT_TRLP       ;Transmit loop
     HLT
;*************************************************
;Opcode is wrong, just halt.
;*************************************************
     EVEN
OPCODE_TRAP:
     LEA     BX, BAD_TRAP_MSG ;Output message
     MOV     AL, [BX]        ;Get characters
BTRP_TRLP:
```

```
     MOV     DX, SIO_DATA     ;Set up to output to 510 data port
     OUT     DX, AL           ;Write the data to the 510
     INC     BX               ;Increment pointer
     MOV     AL, [BX]         ;Get next character
     TEST    AL, EOT          ;Is it the end?
     JNZ     BTRP_TRLP        ;Transmit loop
     HLT
;*********************************************************
; General Message Area
;*********************************************************

    EVEN
BAD_INPUT_MSG   DB CR,LF,'KEY BOARD INPUT IS BAD, PLEASE USE PROPER
CHOICE',CR,LF,EOT
MENU_MSG        DB LF,CR
          DB '***********************************************',LF,CR
          DB 'WELCOME TO PCMCIA-186 INTERFACE',LF,CR
          DB ' TO CHECK SYSTEM FUNCTIONALITY,',LF,CR
          DB ' ENTER ANY OF THE FOLLOWING CHOICE.',LF,CR,LF,CR
          DB ' 1. FOR RAM TEST',CR,LF
          DB ' 2. FOR READING FROM PCMCIA CARD',CR,LF
          DB ' 3. FOR WRITING TO PCMCIA CARD',CR,LF
          DB ' 4. EXIT', CR, LF
          DB '***********************************************',CR,LF
          DB ' >  ',EOT
RAM_OK_MSG      DB CR,LF,'RAM TESTED OK. GOOD JOB ! ',CR,LF,EOT
BAD_RAM_MSG     DB CR,LF,'RAM TESTED BAD, RESET SYSTEM! GOOD LUCK ! ',LF,CR,EOT
BAD_INT_MSG     DB CR,LF,'UN-WANTED INTERRUPTS HAPPENED, SYTEM HALTED',LF,CR,EOT
BAD_TRAP_MSG    DB CR,LF,'CAN NOT DECIPHER THE OPCODE, SYTEM HALTED!',LF,CR,EOT
HALT_MSG       DB CR,LF,'SYSTEM HALTED AS PER YOUR REQUEST!',EOT
MSG_FAIL       DB CR,LF,'CARD DETECT FAILED.',CR,LF,EOT
CARD_150       DB LF,'CARD SPEED=150ns',EOT
CARD_200       DB LF,'CARD SPEED=200ns',EOT
CARD_250       DB LF,'CARD SPEED=250ns',EOT
CARD_2MEG      DB LF,'CARD SIZE=2Meg Bytes',EOT
CARD_4MEG      DB LF,'CARD SIZE=4Meg Bytes',EOT
CARD_6MEG      DB LF,'CARD SIZE=6Meg Bytes',EOT
CARD_8MEG      DB LF,'CARD SIZE=8Meg Bytes',EOT
CARD_10MEG     DB LF,'CARD SIZE=10Meg Bytes',EOT
CARD_12MEG     DB LF,'CARD SIZE=12Meg Bytes',EOT
CARD_16MEG     DB LF,'CARD SIZE=16Meg Bytes',EOT
CARD_20MEG     DB LF,'CARD SIZE=20Meg Bytes',EOT
UNKNWN_MSG     DB LF,CR,'SPEED UNKNOWN, PLEASE CHECK, MAY BE NON-INTEL CARD',LF,CR
               DB LF,CR,'OR SERIES 1 CARD OR BY DIFFERENT MANUFACTURER',LF,CR,EOT
CARD_MISZ      DB LF,CR,'SIZE UNKNOWN. PLEASE CHECK',EOT
PG_NUM_MSG     DB LF,CR,'PLEASE ENTER THE PAGE NUMBER',CR,LF
               DB LF,CR,'FOR THE ABOVE CARD SIZE IN HEX',CR,LF
               DB LF,CR,'FOLLOWED BY <CR>',LF,CR
               DB LF,CR,'1 MEG = "00F" PAGES AND SO ON..',CR,LF
               DB LF,CR,'UP TO 64 MEG OR "3FF" PAGE',CR,LF,EOT
BAD_PG_MSG     DB LF,CR,'ENTERED PAGE NUMBER IS INCORRECT',CR,LF
               DB LF,CR,'REFER TO THE INSTRUCTION AND',LF,CR
               DB LF,CR,'RE-TYPE THE VALUE, please',LF,CR,EOT
RD_MSG         DB LF,CR,'CARD READ IS SUCCESSFUL',LF,CR
               DB LF,CR,'WELL DONE, THANK YOU!',LF,CR,EOT
ER_SUC_MSG     DB LF,CR,'SELECTED PAGE WAS SUCCESSFULLY ERASED',LF,CR
```

```
                DB LF,CR,'GREAT JOB, WELL DONE',LF,CR,EOT
ER_UN_MSG       DB LF,CR,'SELECTED PAGE CAN NOT BE ERASED',LF,CR
                DB LF,CR,'PLEASE TRY ANOTHER PAGE OR CHECK THE Vpp',CR,LF,EOT
WR_DONE_MSG     DB CR,LF,'SELECTED PAGE WRITTEN SUCCESSFULLY',LF,CR
                DB CR,LF,'GREAT JOB, WELL DONE',CR,LF,EOT
NO_WR_MSG       DB LF,CR,'CAN NOT WRITE TO THE CARD',LF,CR
                DB LF,CR,'CHECK THE CARD FUNCTIONALITY',CR,LF,EOT
MSG_COUNT       EQU     $-MENU_MSG
CODE    ENDS
;*******************************************************
;     Power-on Reset Code to Get Started
;     No wait state for memory, block size=8 KBytes
;*******************************************************
     ASSUME  CS:POWER_ON

     POWER_ON SEGMENT AT 0FFFFH

PRST:   MOV  DX, UMCS       ;Point to UMCS Register
     MOV  AX, UMCS_VAL      ;Reprogram UMCS to match

     OUT  DX, AL            ;system requirements
     JMP  FW_START          ;Jump to init code

POWER_ON  ENDS
;*************************************************************
;
;     Data Segment
;
;*************************************************************

DATA    SEGMENT PUBLIC  'DATA'
     DD   256 DUP (?)       ;Reserved for Interrupt Vectors

;The definitions of all card codes follow



DATA    ENDS
;*************************************************************
; Program Ends
;*************************************************************

     END  INIT
```